CODE COMPLIANCE

ALL WORK AND MATERIALS SHALL BE PERFORMED AND INSTALLED IN ACCORDANCE WITH THE CURRENT EDITIONS OF THE FOLLOWING CODES AS ADOPTED BY THE LOCAL GOVERNING AUTHORITIES. NOTHING IN THESE PLANS IS TO BE CONSTRUED TO PERMIT WORK NOT CONFORMING TO THESE CODES.

1. CALIFORNIA BUILDING STANDARDS CODE: 2019 TRIENNIAL EDITION OF TITLE 24, WITH AN EFFECTIVE DATE OF JANUARY 1, 2020. PART 1 - CALIFORNIA ADMINISTRATIVE CODE

PART 2 - CALIFORNIA BUILDING CODE, BASED ON THE 2018 INTERNATIONAL BUILDING CODE

PART 2.5 - CALIFORNIA RESIDENTIAL CODE, BASED ON THE 2018 INTERNATIONAL RESIDENTIAL CODE

PART 3 - CALIFORNIA ELECTRICAL CODE, BASED ON THE 2017 NATIONAL ELECTRICAL CODE

PART 4 - CALIFORNIA MECHANICAL CODE, BASED ON THE 2018 UNIFORM MECHANICAL CODE

PART 5 - CALIFORNIA PLUMBING CODE, BASED ON THE 2018

UNIFORM PLUMBING CODE

PART 6 - CALIFORNIA ENERGY CODE

PART 7 - VACANT PART 8 - CALIFORNIA HISTORICAL BUILDING CODE

PART 9 - CALIFORNIA FIRE CODE, BASED ON THE 2018 INTERNATIONAL

PART 10 - CALIFORNIA EXISTING BUILDING CODE, BASED ON THE 2018 INTERNATIONAL EXISTING BUILDING CODE

PART 11 - CALIFORNIA GREEN BUILDING STANDARDS CODE (ALSO KNOWN AS CALGREEN)

PART 12 - CALIFORNIA REFERENCED STANDARDS CODE

- ANSI/TIA-222 (REV H)
- 3. 2018 NFPA 101, LIFE SAFETY CODE
- 4. 2019 NFPA 72, NATIONAL FIRE ALARM AND SIGNALING CODE 5. 2019 NFPA 13, STANDARD FOR THE INSTALLATION OF SPRINKLER SYSTEMS

PROJECT TEAM

APPLICANT / LESSEE:

AT&T MOBILITY SERVICES, LLC 5001 EXECUTIVE PKWY. SAN RAMON, CA 94583 CONTACT: JENNIFER MATHEWS Site Acquisition Manager EMAIL: jm534@att.com PH: (925) 277-6374 CELL: (310) 740-0691

CONSTRUCTION MANAGER:

AT&T MOBILITY SERVICES, LLC 5001 EXECUTIVE PKWY, SAN RAMON, CA 94583 CONTACT: PHUNG NGUYEN Sr. Specialist-Tech Vendor Management Technology Operations EMAIL: phung.nguyen@att.com PH: (925) 277-6480 CELL: (408) 391-0786

RF ENGINEER:

AT&T MOBILITY SERVICES, LLC 5001 EXECUTIVE PKWY SAN RAMON, CA 94583 CONTACT: JOSE PABELONIO RAN ENGINEER EMAIL: jp5720@att.com PH: (949) 344-1628

PROJECT MANAGER, LEASING & ZONING:

J5 INFRASTRUCTURE PARTNERS 1150 BALLENA BLVD. SUITE 259 ALAMEDA, CA 94501 CONTACT: CHARLES OTIS EMAIL: cotis@i5ip.com PH: (805) 680-5453

A&E MANAGER:

J5 INFRASTRUCTURE PARTNERS 2030 MAIN STREET, SUITE 200 **IRVINE, CA 92614** contact: JEFF CLARK email: jclark@j5ip.com ph: (949) 302-9801

SITE INFORMATION

PROPERTY OWNER: CITY OF MORGAN HILL 17555 PEAK AVENUE MORGAN HILL, CA 95037

JURISDICTION: CITY OF MORGAN HILL

773-09-030

CURRENT ZONING: EXISTING USE: MULTIUSE

MULTIUSE, COMMUNICATIONS FACILITY PROPOSED USE: 37.1185250° LATITUDE (NAD 83):

37° 07' 06.69" N LONGITUDE (NAD 83): -121.6698561°

121° 40′ 11.48196″ W

ACCESSIBILITY REQUIREMENTS: FACILITY IS UNMANNED AND NOT FOR HUMAN HABITATION. ACCESSIBILITY IS NOT REQUIRED PER CBC2019, SECTION 11B-203.4 (LIMITED ACCESS SPACE)

POWER AGENCY: PH: (800) 743-5000

TELEPHONE AGENCY:

RFDS VERSION: 2.00 DATE UPDATED: 04/17/20

03/11/20



SITE NUMBER: CCL03263

MORGAN HILL SITE NAME:

STUB POLE - INDOOR EQUIPMENT SITE TYPE:

ADDRESS: 1305 WEST DUNNE AVENUE

MORGAN HILL, CA 95037

APPROVALS

THE FOLLOWING PARTIES HEREBY APPROVE AND ACCEPT THESE DOCUMENTS & AUTHORIZE THE SUBCONTRACTOR TO PROCEED WITH CONSTRUCTION DESCRIBED HEREIN. ALL DOCUMENTS ARE SUBJECT TO REVIEW BY LOCAL BUILDING DEPARTMENT & MAY IMPOSE CHANGES AND MODIFICATIONS.

DISCIPLINE:	SIGNATURE	DATE
RF ENGINEER:		
AT&T PM:		
CIVIL:		
A&E:		
SAQ PM:		
PROPERTY OWNER:		

Vendor:

J5 INFRASTRUCTURE 1150 BALLENA BLVD. UNIT 259

PREPARED FOR

STA (

5001 EXECUTIVE PKWY,

SAN RAMON CA 94583

P-044379

ALAMEDA, CA 94501

AT&T Site ID:

CCL03263

PROJECT DESCRIPTION LOCAL MAP

MODIFICATION TO AN UNMANNED TELECOMMUNICATIONS FACILITY, CONSISTING OF THE FOLLOWING:

- REMOVE (3) PANEL ANTENNAS AT POS. 1, POS. 3 & POS. 4
- REMOVE (1) RRUS 11 B12 FROM NEAR ANTENNAS
- RELOCATE (1) PANEL ANTENNA FROM POS. 2 TO POS. 1 • INSTALL (2) PROPOSED PANEL ANTENNAS AT POS. 2 & POS. 3
- INSTALL (1) PROPOSED RRUS 4449 B5/B12 NEAR POS. 3

- INSTALL (1) CROSS-ARM MOUNT ON EXISTING POLE
- INSTALL (3) PANEL ANTENNAS ON PROPOSED CROSS-ARM MOUNT
- INSTALL (1) RRUS 4478 B14 NEAR POS.2
- INSTALL (1) RRUS 32 B66A NEAR POS. 2
- INSTALL (1) RRUS 32 B30 NEAR POS. 2
- INSTALL (1) RRUS 32 B2 NEAR POS. 3
- INSTALL (1) RRUS 4449 B5/B12 NEAR POS. 3 • INSTALL (1) DC6 BOX ON EXISTING UNISTRUT
- INSTALL (2) #8 AWG DC POWER TRUNKS & (1) FIBER TRUNK IN EXISTING
- EMPTY 4" U/G CONDUIT
- REUSE (4) EXISTING 7/8" COAX CABLES

SECTOR C

all 2 Full Working Days In Advance

- REMOVE (3) PANEL ANTENNAS AT POS. 1, POS. 3 & POS. 4
- REMOVE (1) RRUS 11 B12 FROM NEAR ANTENNAS • RELOCATE (1) PANEL ANTENNA FROM POS. 2 TO POS. 1
- INSTALL (2) PROPOSED PANEL ANTENNAS AT POS. 2 & POS. 3
- INSTALL (1) PROPOSED RRUS 4449 B5/B12 NEAR POS. 3

EQUIPMENT SHELTER:

- REMOVE (2) RRUS 11 B5 FROM EXISTING POST IN SHELTER • INSTALL (1) RRUS E2 B29 ON EXISTING POST IN SHELTER FOR
- **NEW B SECTOR**
- INSTALL (1) 6630 BBU IN EXISTING RACK IN SHELTER

• INSTALL (2) RECTIFIERS IN EXISTING DC POWER PLANT IN SHELTER

SHEET INDEX

DO NOT SCALE DRAWINGS

USID: 13100

FA#: 10095723

PTN#:3701A0TZ45

PACE#: MRSFR071172

SECTOR ADD- 3RD SECTOR

THESE PLANS ARE FORMATTED TO BE FULL SIZE AT 24" X 36". CONTRACTORS SHALL VERIFY ALL PLANS AND EXISTING DIMENSIONS AND CONDITIONS ON THE JOB SITE AND SHALL IMMEDIATELY NOTIFY THE ARCHITECT/ENGINEER IN WRITING OF ANY DISCREPANCIES BEFORE PROCEEDING WITH THE WORK OR MATERIAL ORDERS OR BE RESPONSIBLE FOR THE SAME.

GENERAL CONTRACTOR NOTES

VICINITY MAP

GENERAL NOTES

THE FACILITY IS UNMANNED AND NOT FOR HUMAN HABITATION. A TECHNICIAN WILL VISIT THE SITE AS REQUIRED FOR ROUTINE MAINTENANCE. THE PROJECT WILL NOT RESULT IN ANY SIGNIFICANT DISTURBANCE OR EFFECT ON DRAINAGE; NO SANITARY SEWER SERVICE, POTABLE WATER, OR TRASH DISPOSAL IS REQUIRED AND NO COMMERCIAL SIGNAGE IS PROPOSED.

STATEMENTS

STRUCTURAL ANALYSIS IS NOT WITHIN THE SCOPE OF WORK CONTAINED IN THIS DRAWINGS SET. FOR ANALYSIS OF EXISTING AND/OR PROPOSED COMPONENTS, REFER TO STRUCTURAL ANALYSIS PROVIDED UNDER SEPARATE COVER.


ANTENNA MOUNT ANALYSIS IS NOT WITHIN THE SCOPE OF WORK CONTAINED IN THIS DRAWING SET. FOR ANALYSIS OF MOUNT TO SUPPORT EXISTING AND/OR PROPOSED COMPONENTS, REFER TO ANTENNA MOUNT STRUCTURAL ANALYSIS PROVIDED UNDER SEPARATE COVER.

DIRECTIONS FROM AT&T OFFICE: 5001 EXECUTIVE PKWY, SAN RAMON CA 94583

1. GET ON I-680 S FROM EXECUTIVE PKWY, CAMINO RAMON AND BOLLINGER CANYON RD

DRIVING DIRECTIONS

- 2. HEAD SOUTHWEST
- 3. TURN RIGHT
- 4. TURN LEFT TOWARD EXECUTIVE PKWY
- 5. TURN RIGHT TOWARD EXECUTIVE PKWY
- 6. TURN RIGHT ONTO EXECUTIVE PKWY
- 7. TURN RIGHT ONTO CAMINO RAMON
- 8. USE THE RIGHT 2 LANES TO TURN RIGHT ONTO BOLLINGER CANYON RD
- 9. USE THE RIGHT LANE TO MERGE ONTO I-680 S VIA THE RAMP TO SAN JOSE
- 10. FOLLOW I-680 S AND US-101 S TO E DUNNE AVE IN MORGAN HILL
- 11. TAKE THE EAST DUNNE AVE EXIT FROM US-101 S
- 12. MERGE ONTO I-680 S
- 13. USE THE RIGHT 3 LANES TO MERGE ONTO US-101 S TOWARD LOS ANGELES
- 14. TAKE THE EAST DUNNE AVE EXIT TOWARD MORGAN HILL
- 15. TURN RIGHT ONTO E DUNNE AVE



D-1 DETAILS D-2 DETAILS

EME-EME SIGNAGE LOCATION PLAN DIGALFRT

GROUNDING DETAILS

SOUTHEAST ELEVATIONS PLUMBING DIAGRAM **GROUNDING PLAN & NOTES**

It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

08/03/20 COLORED ELEV MM3

No. 89570

REV DATE DESCRIPTION

Licensor:

100% CD

90% CD

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

TITLE SHEET

Sheet Number:

T - 1

GENERAL CONSTRUCTION NOTES:

- 1. PLANS ARE INTENDED TO BE DIAGRAMMATIC OUTLINE ONLY, UNLESS NOTED OTHERWISE. THE WORK SHALL INCLUDE FURNISHING MATERIALS, EQUIPMENT, APPURTENANCES AND LABOR NECESSARY TO COMPLETE ALL INSTALLATIONS AS INDICATED ON THE DRAWINGS.
- 2. THE CONTRACTOR SHALL OBTAIN, IN WRITING, AUTHORIZATION TO PROCEED BEFORE STARTING WORK ON ANY ITEM NOT CLEARLY DEFINED OR IDENTIFIED BY THE CONTRACT DOCUMENTS.
- 3. CONTRACTOR SHALL CONTACT USA (UNDERGROUND SERVICE ALERT) AT (800) 227-2600, FOR UTILITY LOCATIONS, 48 HOURS BEFORE PROCEEDING WITH ANY EXCAVATION, SITE WORK OR CONSTRUCTION.
- 4. THE CONTRACTOR SHALL INSTALL ALL EQUIPMENT AND MATERIALS IN ACCORDANCE WITH MANUFACTURER'S RECOMMENDATIONS UNLESS SPECIFICALLY INDICATED OTHERWISE, OR WHERE LOCAL CODES OR REGULATIONS TAKE PRECEDENCE.
- 5. ALL CONSTRUCTION SHALL BE IN ACCORDANCE WITH THE CBC / UBC'S REQUIREMENTS REGARDING EARTHQUAKE RESISTANCE, FOR, BUT NOT LIMITED TO, PIPING, LIGHT FIXTURES, CEILING GRID, INTERIOR PARTITIONS, AND MECHANICAL EQUIPMENT. ALL WORK MUST COMPLY WITH LOCAL EARTHQUAKE CODES AND REGULATIONS.
- REPRESENTATIONS OF TRUE NORTH, OTHER THAN THOSE FOUND ON THE PLOT OF SURVEY DRAWINGS, SHALL NOT BE USED TO IDENTIFY OR ESTABLISH BEARING OF TRUE NORTH AT THE SITE. THE CONTRACTOR SHALL RELY SOLELY ON THE PLOT OF SURVEY DRAWING AND ANY SURVEYOR'S MARKINGS AT THE SITE FOR THE ESTABLISHMENT OF TRUE NORTH, AND SHALL NOTIFY THE ARCHITECT / ENGINEER PRIOR TO PROCEEDING WITH THE WORK IF ANY DISCREPANCY IS FOUND BETWEEN THE VARIOUS ELEMENTS OF THE WORKING DRAWINGS AND THE TRUE NORTH ORIENTATION AS DEPICTED ON THE CIVIL SURVEY. THE CONTRACTOR SHALL ASSUME SOLE LIABILITY FOR ANY FAILURE TO NOTIFY THE ARCHITECT / ENGINEER.
- 7. THE BUILDING DEPARTMENT ISSUING THE PERMITS SHALL BE NOTIFIED AT LEAST TWO WORKING DAYS PRIOR TO THE COMMENCEMENT OF WORK, OR AS OTHERWISE STIPULATED BY THE CODE ENFORCEMENT OFFICIAL HAVING JURISDICTION.
- 8. DO NOT EXCAVATE OR DISTURB BEYOND THE PROPERTY LINES OR LEASE LINES, UNLESS OTHERWISE NOTED.
- 9. ALL EXISTING UTILITIES, FACILITIES, CONDITIONS, AND THEIR DIMENSIONS SHOWN ON THE PLAN HAVE BEEN PLOTTED FROM AVAILABLE RECORDS. THE ARCHITECT / ENGINEER AND THE OWNER ASSUME NO RESPONSIBILITY WHATSOEVER AS TO THE SUFFICIENCY OR THE ACCURACY OF THE INFORMATION SHOWN ON THE PLANS, OR THE MANNER OF THEIR REMOVAL OR ADJUSTMENT. CONTRACTORS SHALL BE RESPONSIBLE FOR DETERMINING EXACT LOCATION OF ALL EXISTING UTILITIES AND FACILITIES PRIOR TO START OF CONSTRUCTION. CONTRACTORS SHALL ALSO OBTAIN FROM EACH UTILITY COMPANY DETAILED INFORMATION RELATIVE TO WORKING SCHEDULES AND METHODS OF REMOVING OR ADJUSTING EXISTING UTILITIES.
- 10. CONTRACTOR SHALL VERIFY ALL EXISTING UTILITIES, BOTH HORIZONTAL AND VERTICALLY, PRIOR TO THE START OF CONSTRUCTION. ANY DISCREPANCIES OR DOUBTS AS TO THE INTERPRETATION OF PLANS SHOULD BE IMMEDIATELY REPORTED TO THE ARCHITECT / ENGINEER FOR RESOLUTION AND INSTRUCTION, AND NO FURTHER WORK SHALL BE PERFORMED UNTIL THE DISCREPANCY IS CHECKED AND CORRECTED BY THE ARCHITECT / ENGINEER. FAILURE TO SECURE SUCH INSTRUCTION MEANS CONTRACTOR WILL HAVE WORKED AT HIS/HER OWN RISK AND EXPENSE.
- 11. ALL NEW AND EXISTING UTILITY STRUCTURES ON SITE AND IN AREAS TO BE DISTURBED BY CONSTRUCTION SHALL BE ADJUSTED TO FINISH ELEVATIONS PRIOR TO FINAL INSPECTION OF WORK.
- 12. ANY DRAIN AND/OR FIELD TILE ENCOUNTERED / DISTURBED DURING CONSTRUCTION SHALL BE RETURNED TO IT'S ORIGINAL CONDITION PRIOR TO COMPLETION OF WORK, SIZE, LOCATION AND TYPE OF ANY UNDERGROUND UTILITIES OR IMPROVEMENTS SHALL BE ACCURATELY NOTED AND PLACED ON "AS-BUILT" DRAWINGS BY GENERAL CONTRACTOR, AND ISSUED TO THE ARCHITECT / ENGINEER AT COMPLETION OF PROJECT.
- 13. ALL TEMPORARY EXCAVATIONS FOR THE INSTALLATION OF FOUNDATIONS, UTILITIES, ETC., SHALL BE PROPERLY LAID BACK OR BRACED IN ACCORDANCE WITH CORRECT OCCUPATIONAL SAFETY AND HEALTH ADMINISTRATION (OSHA) REQUIREMENTS
- 14. INCLUDE MISC. ITEMS PER AT&T SPECIFICATIONS

APPLICABLE CODES, REGULATIONS AND STANDARDS:

- 1. SUBCONTRACTOR'S WORK SHALL COMPLY WITH ALL APPLICABLE NATIONAL, STATE, AND LOCAL CODES AS ADOPTED BY THE LOCAL AUTHORITY HAVING JURISDICTION (AHJ) FOR THE LOCATION.
- 2. THE EDITION OF THE AHJ ADOPTED CODES AND STANDARDS IN EFFECT ON THE DATE OF CONTRACT AWARD SHALL GOVERN THE DESIGN.
- 3. SUBCONTRACTOR'S WORK SHALL COMPLY WITH THE LATEST EDITION OF THE FOLLOWING STANDARDS:
- AMERICAN CONCRETE INSTITUTE (ACI) 318, BUILDING CODE REQUIREMENTS FOR STRUCTURAL CONCRETE
- AMERICAN INSTITUTE OF STEEL CONSTRUCTION (AISC), MANUAL OF STEEL CONSTRUCTION, ASD, FIFTEENTH EDITION
- TELECOMMUNICATIONS INDUSTRY ASSOCIATION (TIA) 222-H, STRUCTURAL STANDARD FOR STRUCTURAL ANTENNA TOWER AND ANTENNA SUPPORTING STRUCTURES
- INSTITUTE FOR ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE) 81, GUIDE FOR MEASURING EARTH RESISTIVITY, GROUND IMPEDANCE, AND EARTH SURFACE POTENTIALS OF A GROUND SYSTEM IEEE 1100 (1999) RECOMMENDED PRACTICE FOR POWERING AND GROUNDING OF ELECTRICAL EQUIPMENT.
- 3.5. IEEE C62.41, RECOMMENDED PRACTICES ON SURGE VOLTAGES IN LOW VOLTAGE AC POWER CIRCUITS (FOR LOCATION CATEGORY "C3" AND "HIGH SYSTEM EXPOSURE")
- TIA 607 COMMERCIAL BUILDING GROUNDING AND BONDING REQUIREMENTS FOR TELECOMMUNICATIONS TELCORDIA GR-63 NETWORK
- EQUIPMENT-BUILDING SYSTEM (NEBS): PHYSICAL PROTECTION
- TELCORDIA GR-347 CENTRAL OFFICE POWER WIRING
- TELCORDIA GR-1275 GENERAL INSTALLATION REQUIREMENTS
- TELCORDIA GR-1503 COAXIAL CABLE CONNECTIONS
- 3.11. ANY AND ALL OTHER LOCAL & STATE LAWS AND REGULATIONS
- 3.12. FOR ANY CONFLICTS BETWEEN SECTIONS OF LISTED CODES AND STANDARDS REGARDING MATERIAL, METHODS OF CONSTRUCTION, OR OTHER REQUIREMENTS, THE MOST RESTRICTIVE SHALL GOVERN. WHERE THERE IS CONFLICT BETWEEN A GENERAL REQUIREMENT AND A SPECIFIC REQUIREMENT, THE SPECIFIC REQUIREMENT SHALL GOVERN.

A RRDE\/IATIONIC

	ABBREVIATIONS:					
ANCHOR BOLT	FDN.	FOUNDATION				
ABOVE	F.O.C.	FACE OF CONCRETE				
ANTENNA CABLE COVER ASSEMBLY	F.O.M.	FACE OF MASONRY				
ADDITIONAL	F.O.S.	FACE OF STUD				
ABOVE FINISHED FLOOR	F.O.W.	FACE OF WALL				
ABOVE FINISHED GRADE	F.S.	FINISH SURFACE				
ALUMINUM	FT.(')	FOOT (FEET)				
ALTERNATE	FTG.	FOOTING				
ANTENNA	G.	GROWTH (CABINET)				
APPROXIMATE(LY)	GA.	GAUGE				
ARCHITECT(URAL)	GI.	GALVANIZE(D)				
AMERICAN WIRE GAUGE	G.F.I.	GROUND FAULT CIRCUIT				
BUILDING	INTERRUPTER	CROOND I / ROLL CIRCOII				
BLOCK	GLB. (GLU-LAM)	GLUE LAMINATED BEAM				
BLOCKING	GPS	GLOBAL POSITIONING SYSTEM				
BEAM	GRND.	GROUND				
BOUNDARY NAILING	HDR.	HEADER				
BARE TINNED COPPER WIRE	HGR.	HANGER				
BOTTOM OF FOOTING	HT.	HEIGHT				
BACK-UP CABINET	ICGB.	ISOLATED COPPER GROUND BUS				
CABINET	IN. (")	INCH(ES)				
CANTILEVER(ED)	INT.	INTERIOR				
CAST IN PLACE	LB.(#)	POUND(S)				
CEILING	L.B.	LAG BOLTS				
CLEAR	L.F.	LINEAR FEET (FOOT)				
COLUMN	L.	LONG(ITUDINAL)				
CONCRETE	MAS.	MASONRY				
CONNECTION(OR)	MAX.	MAXIMUM				
CONSTRUCTION	M.B.	MACHINE BOLT				
CONTINUOUS	MECH.	MECHANICAL				
PENNY (NAILS)	MFR.	MANUFACTURER				
DOUBLE	MIN.	MINIMUM				
DEPARTMENT	MISC.	MISCELLANEOUS				
DOUGLAS FIR	MTL.	METAL				
DIAMETER	(N)	NEW				
DIAGONAL	NO.(#)	NUMBER				
DIMENSION	N.T.S.	NOT TO SCALE				
DRAWING(S)	O.C.	ON CENTER				
DOWEL(S)	OPNG.	OPENING				
EACH	P/C	PRECAST CONCRETE				
ELEVATION	PCS	PERSONAL COMMUNICATION				
ELECTRICAL	SERVICES					
ELEVATOR	PLY.	PLYWOOD				
ELECTRICAL METALLIC TUBING	PPC	POWER PROTECTION CABINET				
EDGE NAIL	PRC	PRIMARY RADIO CABINET				
ENGINEER	P.S.F.	POUNDS PER SQUARE FOOT				
EQUAL	P.S.I.	POUNDS PER SQUARE INCH				
EXPANSION	P.T.	PRESSURE TREATED				
EXISTING	PWR.	POWER (CABINET)				
EXTERIOR FARRICATION (OR)	QTY.	QUANTITY				
FABRICATION(OR)	RAD.(R)	RADIUS				

REQ'D/

	SCH. SHT. SIM. SPEC. SQ. S.S. STD. STL. STRUC. TEMP. THK. T.N.	SCHEDULE SHEET SIMILAR SPECIFICATIONS SQUARE STAINLESS STEEL STANDARD STEEL STRUCTURAL TEMPORARY THICK(NESS) TOE NAIL
	T.O.A.	TOP OF ANTENNA
OTE :	T.O.C.	TOP OF CURB
STEM	T.O.F. T.O.P. T.O.S. T.O.W. TYP.	TOP OF FOUNDATION TOP OF PLATE (PARAPET) TOP OF STEEL TOP OF WALL TYPICAL
nd bus	U.G. U.L. U.N.O. V.I.F. W W/ WD. W.P. WT	UNDER GROUND UNDERWRITERS LABORATORY UNLESS NOTED OTHERWISE VERIFY IN FIELD WIDE (WIDTH) WITH WOOD WEATHERPROOF WEIGHT CENTERLINE PLATE, PROPERTY LINE

SYMBOLS LEGEND:

FINISH FLOOR

FINISH GRADE

FINISH(ED)

FLOOR

A.B.

ABV.

ACCA

ADD'L

A.F.G.

ALUM.

ALT.

ANT.

APPRX.

ARCH.

AWG.

BLDG.

BLK.

BM.

B.N.

B.O.F. B/U

CAB.

CANT. C.I.P.

CLG.

CLR. COL.

CONC.

CONN.

CONST.

CONT.

DBL.

DEPT.

D.F.

DIA.

DIAG.

DIM.

DWL. EA.

ELEC.

ELEV.

EMT.

E.N.

ENG.

EQ.

EXP.

FIN.


FLR.

EXST.(E)

DWG.

BLKG.

A.F.F.



REFERENCE

REQUIRED

REINFORCEMENT(ING)

RIGID GALVANIZED STEEL

PREPARED FOR



5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:




P-044379

1150 BALLENA BLVD. UNIT 259

ALAMEDA, CA 94501

AT&T Site ID:

CCL03263



Licensor:



It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

GENERAL NOTES

Sheet Number:

GN-



This Site Operated by:

AT&T MOBILITY

5001 EXECUTIVE PKWY SAN RAMON, CA 94583 IN CASE OF FIRE AND THE NEED FOR SHUTDOWN TO DEACTIVATE ANTENNAS CALL THE FOLLOWING NUMBER:

For 24 Hour Emergency Contact and Access Please Call:

Reference Site#: CCL03263

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

FENCED COMPOUND SIGNAGE



FENCED COMPOUND SIGNAGE



DOOR / EQUIPMENT SIGN



DIESEL FUEL NO SMOKING NO OPEN FLAMES

LEAD ACID BATTERIES CORROSIVE LIQUIDS (ELECTROLYTE) **ENERGIZED ELECTRICAL CIRCUITS** NO SMOKING

INFORMATION

Federal Communications Communication Tower Registration Number

Posted in accordance with federal Communications Commission rules and antenna tower registration 47CFR 17.4(g).

FCC ASR SIGNAGE N.T.S.

Property of AT&T

Authorized Personnel Only

No Trespassing Violators will be Prosecuted

In case of emergency, or prior to performing maintenance on this site, call and reference cell site number

GATE SIGNAGE

Property of AT&T

Authorized Personnel Only

In case of emergency, or prior to performing maintenance on this site, call and reference cell site number





AT&T operates antennas at this site. **Beyond This Point** you are entering an area where radio frequency (RF) fields may exceed the FCC General Population Exposure Limits. Follow safety guidelines for working in an RF Contact AT&T at 800-638-2822, option 9 and 3, and follow their instructions prior to performing any maintenance or repairs above this point.

(8" x 12")

A CAUTION

Radio frequency (RF) fields near some antennas

follow their instructions prior to performing

maintenance or repairs beyond this point.

may exceed the FCC Occupational Exposure Limits

Contact AT&T at 800-638-2822, option 9 and 3, and

Personnel climbing this tower should be trained

for working in RF environments and use a personal

RF monitor if working near active antennas.

Contine Sign (CARTY OK-10,7) This is ATST site

Caution Sign 2B Tower

 $(8'' \times 12'')$

Use for Towers only

Notice Sign 2

On this tower:

EDITION.

FABRICATION:





AT&T operates antennas at this site Beyond This Point you are entering an area where radio frequency (RF) fields may exceed the FCC Occupational Exposure Limits. Follow safety guidelines for working in an RF

Contact AT&T at 800-638-2822, option 9 and 3, and folicy their instructions prior to performing maintenance or repairs beyond this point. · teams on section of This is \$181 side_

> Caution Sign 2 (8" x 12")

ACAUTION

AT&T operates antennas at this site.

FCC Occupational Exposure Limits.

Quantification, our This is AT&T site _____

environment.

Seyond This Point you are entering an area

Follow safety guidelines for working in an RF

Contact AT&T at 808-638-2822, option 9 and 3,

and follow their instructions pilor to performing

Caution Sign 2C Parapet

 $(5'' \times 7'')$

maintenance or regains beyond this point.

where radio frequency (RF) fields may exceed the

A CAUTION



AT&T operates antennas at this site. In The Striped Area you are entering an area where radio frequency (RF) fields may exceed the FCC Occupational Exposure Limits. Follow safety guidelines for working in an RF

Contact AT&T at 800-638-3822, option 9 and 3, and follow their instructions prior to performing maintenance or repairs within the striped area.

Greeten Signe MATERIA . 128 INS 18 A . ET SER.

Caution Sign 2A (8" x 12") Use only if instructed by RF Safety THE FOLLOWING INFORMATION IS A GUIDELINE W/ RESPECT RADIO FREQUENCY ENERGY AND SHOULD BE USED AS FEDERAL GUIDELINES OR REGULATIONS SHOULD BE IN CONFLICT w/ ANY PART OF THESE NOTES OR PLANS, THE MORE RESTRICTIVE GUIDELINE OR REGULATION SHALL BE FOLLOWED AND OVERRIDE THE LESSER.

THE PUBLIC LIMIT OF RF EXPOSURE ALLOWED BY AT&T IS ALLOWED BY AT&T IS 5mWcm*2

IF THE BOTTOM OF THE ANTENNA IS MOUNTED (8) EIGHT FEET EXCEED THE PUBLIC LIMIT OF RF EXPOSURE LIMIT THEN NO

IF THE PUBLIC LIMIT OF RF EXPOSURE ON THE SITE IS EXCEEDED AND THE AREA IS PUBLICLY ACCESSIBLE (e.g. ROOF ACCESS DOOR THAT CANNOT BE LOCKED, OR FIRE EGRESS) THEN BOTH BARRICADES AND STRIPING SHALL BE BARRICADES AND STRIPING SHALL BE DETERMINED BY THE GUIDELINE FOR PLACEMENT OF SUCH BARRICADES AND STRIPING.

IF THE PUBLIC LIMIT OF RF EXPOSURE ON THE SITE IS EXCEEDED AND THE AREA IS PUBLICLY ACCESSIBLE (e.g. ROOF ACCESS DOOR THAT CANNOT BE LOCKED, OR FIRE EGRESS) THEN BOTH BARRICADES AND STRIPING SHALL BE BARRICADES AND STRIPING SHALL BE PLACED AROUND THE ANTENNAS. THE EXACT EXTENT OF THE BARRICADES & CONSTRUCTION. USE THE PLANS AS A GUIDELINE FOR

PLACEMENT OF SUCH BARRICADES AND STRIPING. ALL TRANSMIT ANTENNAS REQUIRE A THREE LANGUAGE WARNING SIGN WRITTEN IN ENGLISH, SPANISH, AND CHINESE. THIS SIGN SHALL BE PROVIDED TO THE CONTRACTOR Y THE AT&T CONSTRUCTION PROJECT MANAGER AT THE TIME OF CONSTRUCTION. THE LARGER SIGN SHALL BE PLACED IN PLAIN SIGHT AT ALL ROOF ACCESS LOCATIONS AND ON ALL BARRICADES. THE SMALLER SIGN SHALL BE PLACED ON THE ANTENNA ENCLOSURES IN A MANNER THAT IS EASILY SEEN BY ANY PERSON ON THE ROOF. WARNING SIGNS SHALL COMPLY W/ ANSI C95.2 COLOR, SYMBOL, AND CONTENT CONVENTIONS. ALL SIGNS SHALL HAVE AT&T'S NAME AND THE COMPANY CONTACT INFORMATION (e.g. TELEPHONE NUMBER) TO ARRANGE FOR ACCESS TO THE RESTRICTED AREAS. THIS TELEPHONE NUMBER SHALL BE PROVIDED TO THE CONTRACTOR BY THE AT&T CONSTRUCTION PROJECT MANAGER AT THE TIME OF CONSTRUCTION.

PHOTOS OF ALL STRIPING, BARRICADES & SIGNAGE SHALL BE PART OF THE CONTRACTORS CLOSE OUT PACKAGE & SHALL BE TURNED INTO THE AT&T CONSTRUCTION PACKAGE & SHALL BE TURNED INTO THE AT&T CONSTRUCTION PROJECT MANAGER AT THE END OF CONSTRUCTION. STRIPING SHALL BE DONE W/ FADE RESISTANT YELLOW SAFETY PAINT IN A CROSS-HATCH PATTERN AS DETAILED BY THE CONSTRUCTION DRAWINGS. ALL BARRICADES SHALL BE MADE OF AN RF FRIENDLY MATERIAL SO AS NOT TO BLOCK OR INTERFERE w/ THE OPERATION OF THE ANTENNAS. BARRICADES SHALL BE PAINTED W/ FADE RESTRAINT YELLOW SAFETY PAINT. THE CONTRACTOR SHALL PROVIDE ALL RF FRIENDLY BARRICADES NEEDED, & SHALL PROVIDE THE AT&T CONSTRUCTION PROJECT MANAGER W/ A DETAILED SHOP DRAWING OF EACH BARRICADE. UPON CONSTRUCTION

TO PREVAILING STANDARDS LIMITING HUMAN EXPOSURE TO SUCH. IF THE SITE'S EMF REPORT OR ANY LOCAL, STATE OR

1mWcm*2 AND THE OCCUPATIONAL LIMIT OF RF EXPOSURE

ABOVE THE GROUND OR WORKING PLATFORM LINE OF THE PERSONAL COMMUNICATION SYSTEM (PCS) AND DOES NOT STRIPING OR BARRICADES SHOULD BE NEEDED.

PLACED AROUND THE ANTENNAS. THE EXACT EXTENT OF THE EMF REPORT FOR THE SITE DONE BEFORE OR SHORTLY AFTER COMPLETION OF SITE CONSTRUCTION. USE THE PLANS AS A

PLACED AROUND THE ANTENNAS. THE EXACT EXTENT OF THE STRIPING SHALL BE DETERMINED BY THE EMF REPORT FOR THE SITE DONE BEFORE OR SHORTLY AFTER COMPLETION OF SITE

COMPLETION.

PREPARED FOR



5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:

"

| SINFRASTRUCTURE | SINFRAS 1150 BALLENA BLVD. UNIT 259 ALAMEDA, CA 94501

P-044379

AT&T Site ID:

CCL03263

08/03/20 COLORED ELEV MM3 100% CD 90% CD

Licensor:



REV DATE DESCRIPTION

It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

SITE SIGNAGE

Sheet Number:

GN-2

BACK W/ BLACK LETTERING. THE INFORMATION BAND SHALL BE 1.2 INCH SOLID GREEN BAND w. 0.5 INCH HIGH BLACK LETTERING. THE BODY TEXT SHALL BE IN BLACK LETTERING W/0.2 INCH HIGH LETTERS. THE REF LINE SHALL BE IN $\frac{1}{8}$ INCH

SIGN 1 IS TO BE MADE ON THE 50 MIL ALUMINUM SHEETING (SIZE 8

INCHES BY 12 INCHES) W/ FOUR (4) $\frac{1}{4}$ INCH MOUNTING HOLES, ONE

WRAPS. THE MAIN BACKGROUND COLOR IS TO BE WHITE FRONT &

EACH CORNER OF THE SIGN FOR MOUNTING W/ HARDWARE W/ TIE

CONTRACTOR SHALL INSTALL ALL INFORMATION SIGNAGE IN

EXPOSURE POLICY AND RF SAFETY COMPLIANCE PROGRAM, LATEST

ACCORDANCE W/ AT&T WIRELESS DOCUMENT #03-0074, RF

*SIGN I-1: ENTRANCE DOOR, SEE DETAIL 1A, THIS SHEET

THE PLACEMENT OF TEXT SHALL BE DONE IN A MANNER THAT WILL PERMIT EASY READING FROM A DISTANCE OF APPROXIMATELY 6 FEET IN FRONT OF THE SIGN.

ALL PAINT WILL BE BAKED W/ENAMEL W/ UV PROTECTIVE COATING OVER THE FACE OF THE SIGN.

*SIGN 1-2: POLE, SEE DETAIL 1B, THIS SHEET

SIGN 2 MUST BE A NON METALLIC LABEL W/ AN ADHESIVE BACKING. THE LABEL SHALL BE MADE USING VINYL OR SIMILAR WEATHERPROOF MATERIAL, THE LABEL SHALL BE APPROXIMATELY 5X7 INCHES W/ A WHITE BACKGROUND AND BLACK LETTERING. THE GREEN BAND SHALL BE 1.375 INCH IN HEIGHT & THE LETTERING SHALL BE BLACK W/ 0.75 INCH HIGH LETTERS. THE TEXT LETTERING SHALL BE BLACK w/ $\frac{1}{8}$ INCH HIGH LETTERS. UV PROTECTION SHALL BE PLACED OVER THE FRONT OF

*SIGN 1-3: BACK OF ANTENNAS, SEE DETAIL 1C & 3, THIS SHEET

*SIGN 3 IS A 1 INCH X 2 INCH PANEL THAT CAN BE APPLIED TO THE BACK OR SIDE OF AN ANTENNA TO IDENTIFY IT AS AN AT&T ANTENNA.

*SIGN 1-4; SIDE OF ANTENNAS, SEE DETAIL 1D & 3, THIS SHEET


SIGN 4 IS MADE FROM TRANSPARENT MATERIAL 1-1/2 INCHES WIDE & 24 INCHES LONG. THE LETTERING IS TO BE BLACK w_2^{\perp} INCH LETTERING IN A VERTICAL COLUMN. THE SPACING BETWEEN WORDS MUST BE SUCH THAT IT IS EASILY READ & FILLS THE LENGTH OF THE SIGN.


NFPA HAZARD SIGN - TYPICAL


SHELTER / CABINET DOORS SIGNAGE $4)_{\overline{N.T.S.}}$

ALERTING & INFORMATION SIGNAGE

GENERAL NOTES







NOTES TO CONTRACTOR:

- 1. CONTRACTOR IS TO REFER TO AT&T'S MOST CURRENT RADIO FREQUENCY DATA SHEET
- (RFDS) PRIOR TO CONSTRUCTION.
 2. CABLE LENGTHS WERE DETERMINED BASED ON VISUAL INSPECTION DURING SITE-WALK. CONTRACTOR TO VERIFY ACTUAL LENGTH DURING PRE-CONSTRUCTION WALK.
- 3. CONTRACTOR TO VERIFY PORTS HAVE SUFFICIENT ROOM.

(E) ANTENNA AZIMUTHS ARE ESTIMATED AND ARE TO BE VERIFIED BY RF.

	Antenna Use Existing/ Type Technology			RRU, TMA, Diplexer, Etc. Existing Final			Additional Antenna Information		nation	Line Information							
Position							Azimuth RAD Cente		Center			Power/Fiber					
	Swap/New	Existing	Final	Existing	Final	Туре	Location	Туре	Location	Existing	Final	Existing	Final	Existing	Final	Existing	Final
						ALPHA											
	SWAP	QUINTEL	COMMSCOPE	LTE 700 DE	LTE 700 DE	RRUS E2 B29	воттом	RRUS E2 B29	воттом								
_		QS8658-3	JAHH-65C-R3B-V3	UMTS 850	UMTS 850												
1										38	38	11	11				
	SWAP	COMMSCOPE	COMMSCOPE	LTE 700 ENET	LTE 700 FNET	RRUS 4478 B14	ТОР	RRUS 4478 B14	ТОР					1			
	JOVAF																
2		JAHH-65C-R3B-V3	NNH4-65C-R6-V3	LTE AWS	LTE WGS	RRUS 32 B66A	TOP	RRUS 32 B66A	TOP	38	38	11	11				
					LTE WCS			RRUS 32 B30	ТОР								
														4			
	SWAP	COMMSCOPE	COMMSCOPE	LTE 850	LTE 700 BC/5G 850	RRUS 11 B5	воттом	RRUS 4449 B5/B12	TOP								
3		JAHH-65C-R3B-V3	NNHH-65C-R4	LTE WCS	LTE 1900	RRUS 32 B30	TOP	RRUS 32 B2	TOP	38	38	11	11				
3										36	36	11	1 11				
	REMOVE	COMMSCOPE	N/A	LTE 700 BC	N/A	RRUS 11 B12	ТОР	N/A	N/A					1			
		SBNHH-1D65C		LTE 1900		RRUS 32 B2	ТОР	·									
4										38	N/A	11	N/A				
	L					BETA								┧			
	NEW	N/A	COMMSCOPE	N/A	LTE 700 DE	N/A	N/A	RRUS E2 B29	воттом	Τ		T		1			_
	INCAA	IN/A		IN/A		IN/A	IN/A	INNOS EZ BZ9	BOTTOW							(S +	\ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \
1			JAHH-65C-R3B-V3		UMTS 850					N/A	70	N/A	11	ES ES	ES ES	Ž s	l È s
														LES	ABLES	ER TRUNKS RUNKS	X X
														AB C C	AB CC	ER .	C POWER TRUNKS - FIBER TRUNKS
	NEW	N/A	COMMSCOPE	N/A	LTE 700 FNET	N/A	N/A	RRUS 4478 B14	TOP					× ×	× ×		×
2			NNH4-65C-R6-V3		LTE AWS			RRUS 32 B66A	TOP	NI/A	70	NI/A	11	OAX	COAX 4" COA	POV	PC BE
2					LTE WCS			RRUS 32 B30	TOP	N/A	70	N/A	11	"" C /4"		DC 1. FI	DC 4' F
														7/8	7/8'	VG [VG 1/4
	NEW	N/A	COMMSCOPE	N/A	LTE 700 BC/5G 850	N/A	N/A	RRUS 4449 B5/B12	ТОР					(12)	(12)	AWG (2) 1/4	AWG (3) 1/4
		.,,	NNHH-65C-R4	','	LTE 1900			RRUS 32 B2	TOP					(1)	(1)	8#	% #
3			THAT SEE AT					111100 02 02		N/A	70	N/A	11			(4)	(9)
	<u> </u>				<u> </u>	GAMMA								1			
	USE	QUINTEL	QUINTEL	LTE 700 DE	LTE 700 DE	RRUS E2 B29	воттом	RRUS E2 B29	воттом					┨			
		,				IKKUS EZ DZ9	BOTTOM	RRUS EZ BZ9	BOTTON								
1	EXISTING	QS8658-3	QS8658-3	UMTS 850	UMTS 850					160	160	11	11				
												1		1			
	SWAP	COMMSCOPE	COMMSCOPE	LTE 700 FNET	LTE 700 FNET	RRUS 4478 B14	TOP	RRUS 4478 B14	ТОР								
2		JAHH-65C-R3B-V3	NNH4-65C-R6-V3	LTE AWS	LTE AWS	RRUS 32 B66A	TOP	RRUS 32 B66A	TOP	160	160	11	11				
2					LTE WCS			RRUS 32 B30	TOP	160	100	11	11				
	SWAP	COMMSCOPE	COMMSCOPE	LTE 850	LTE 700 BC/5G 850	RRUS 11 B5	воттом	RRUS 4449 B5/B12	ТОР			1		1			
		JAHH-65C-R3B-V3		LTE WCS		RRUS 32 B30	ТОР	RRUS 32 B2	TOP								
3										160	160	11	11				
	DENACY (5	CO B 4B 4CCC DE	N1 / 0		N/ A	DD116 44 B42	TOD	N1/A				1		-			
	REMOVE	COMMSCOPE	N/A		N/A	RRUS 11 B12	TOP	N/A	N/A								
4		SBNHH-1D65C		LTE 1900		RRUS 32 B2	TOP			160	N/A	11	N/A				
-r																	
														1			

PREPARED FOR



5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:

J5 INFRASTRUCTURE 1150 BALLENA BLVD. UNIT 259

ALAMEDA, CA 94501 P-044379

AT&T Site ID:

CCL03263

2 08/03/20 COLORED ELEV MM3 1 05/21/20 EME REPORT 0 05/05/20 100% CD A 04/15/20 90% CD REV DATE DESCRIPTION INT.

Licensor:



It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263


MORGAN HILL


1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037


Sheet Title:

PROPOSED RF SCHEDULE

Sheet Number:







PREPARED FOR

Vendor:

J5 INFRASTRUCTURE 1150 BALLENA BLVD. UNIT 259 ALAMEDA, CA 94501 P-044379

AT&T Site ID:

CCL03263

2 | 08/03/20 | COLORED ELEV | MM3 05/21/20 EME REPORT 05/05/20 90% CD REV DATE DESCRIPTION

Licensor:



It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

DETAILS

Sheet Number:

NOTES TO CONTRACTOR: CONTRACTOR IS TO REFER TO AT&T'S MOST CURRENT RADIO FREQUENCY DATA SHEET (RFDS) PRIOR TO CONSTRUCTION. 1150 BALLENA BLVD. UNIT 259 ALPHA G A M M A BETA POS1:LTE 700DE/ POS2:LTE 700FNET/ POS3:LTE 700BC/5G POS1:LTE 700DE/ POS2:LTE 700FNET/ POS3:LTE 700BC/5G POS1:LTE 700DE/ POS2:LTE 700FNET/ POS3:LTE 700BC/5G UMTS 850 LTE AWS/LTE WCS UMTS 850 LTE AWS/LTE WCS **UMTS 850** LTE AWS/LTE WCS LTE UMTS LTE UMITS 700DE 850 LTE UMTS 700DE 850 18 pr FIBER 18 pr FIBER TRUNKS TRUNKS Important Note: For detailed radio to antenna wiring refer to the 18 pr FIBER TRUNKS latest 4T4R Antenna/radio Port connections Field Notice (RF-HW-2016-265) and the 4T Wiring Playbook. TARA TERE TORC UMTS 3 06 BTS UMTS 3 06 BTS 1x5216 + 1x XMU + 1x6630 (Mixed Mode) + 1xXMU IDle (Duple wed) (Duple xed) PLUMBING DIAGRAM

PREPARED FOR

5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:

15 INFRASTRUCTURE

ALAMEDA, CA 94501

P-044379

AT&T Site ID:

CCL03263

2 08/03/20 COLORED ELEV MM3 100% CD 90% CD REV DATE DESCRIPTION INT.

Licensor:



It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

PLUMBING DIAGRAM

Sheet Number:

RF-1

RECOMMENDATIONS:

AT&T SECTOR A

TO BE INSTALLED: A 12' x 20' WIDE PHYSICAL BARRIER WITH CAUTION 2 SIGN

ON EACH POST OF THE PHYSICAL BARRIER EVERY 8' APART.


AT&T SECTOR B

TO BE INSTALLED: A 10' x 16' x 20' PHYSICAL BARRIER WITH CAUTION 2 SIGN ON EACH POST OF THE PHYSICAL BARRIER EVERY 8' APART.

AT&T SECTOR C

TO BE INSTALLED: A 12' x 18' WIDE PHYSICAL BARRIER WITH CAUTION 2 SIGN ON EACH POST OF THE PHYSICAL BARRIER EVERY 8' APART.

RF SAFETY MEASURES COMPLETED PER EME REPORT COMPLETED ON 05/15/2020, BY "OSC ENGINEERING INC." ANY OTHER RF REPORT IS FOR REFERENCE ONLY.



PREPARED FOR



5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:



ALAMEDA, CA 94501

P-044379

AT&T Site ID:

CCL03263

2 | 08/03/20 | COLORED ELEV | MM3 05/21/20 EME REPORT 0 05/05/20 A 04/15/20 90% CD REV DATE DESCRIPTION INT

Licensor:



It is a violation of law for any persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

EME SIGNAGE LOCATION PLAN

Sheet Number:

EME-1

GROUNDING NOTES:


- 1. ALL DETAILS ARE SHOWN IN GENERAL TERMS. ACTUAL GROUNDING INSTALLATION REQUIREMENTS AND CONSTRUCTION ACCORDING TO SITE CONDITIONS.
- 2. ALL GROUNDING CONDUCTORS: #2 AWG SOLID BARE TINNED COPPER WIRE UNLESS OTHERWISE NOTED.
- 3. GROUND BAR LOCATED IN BASE OF EQUIPMENT WILL BE PROVIDED, FURNISHED AND INSTALLED BY THE VENDOR.
- 4. ALL BELOW GRADE CONNECTIONS: EXOTHERMIC WELD TYPE, ABOVE GRADE CONNECTIONS: EXOTHERMIC WELD TYPE.
- 5. GROUND RING SHALL BE LOCATED A MINIMUM OF 24" BELOW GRADE OR 6" MINIMUM BELOW THE FROST LINE.
- 6. INSTALL GROUND CONDUCTORS AND GROUND ROD MINIMUM OF 1'-0" FROM EQUIPMENT CONCRETE SLAB, SPREAD FOOTING, OR FENCE.
- 7. EXOTHERMIC WELD GROUND CONNECTION TO FENCE POST: TREAT WITH A COLD GALVANIZED SPRAY.
- 8. GROUND BARS:
 - A) EQUIPMENT GROUND BUS BAR (EGB) LOCATED AT THE BOTTOM OF ANTENNA POLE/MAST FOR MAKING GROUNDING JUMPER CONNECTIONS TO COAX FEEDER CABLES SHALL BE FURNISHED AND INSTALLED BY ELECTRICAL CONTRACTOR. JUMPERS (FURNISHED BY OWNERS) SHALL BE INSTALLED AND CONNECTED BY ELECTRICAL CONTRACTOR.
- 9. ALL GROUNDING INSTALLATIONS AND CONNECTIONS SHALL BE MADE BY ELECTRICAL CONTRACTOR.
- 10. OBSERVE N.E.C. AND LOCAL UTILITY REQUIREMENTS FOR ELECTRICAL SERVICE GROUNDING.
- 11. GROUNDING ATTACHMENT TO TOWER SHALL BE AS PER MANUFACTURER'S RECOMMENDATIONS OR AT GROUNDING POINTS PROVIDED (2 MINIMUM).
- 12. IF EQUIPMENT IS IN A C.L. FENCE ENCLOSURE, GROUND ONLY CORNER POSTS AND SUPPORT POSTS OF GATE. IF CHAIN LINK LID IS USED, THEN GROUND LID ALSO.
- 13. GROUNDING AT PPC CABINET SHALL BE VERTICALLY INSTALLED.
- 14. ALL GROUNDING FOR ANTENNAS SHALL BE CONNECTED SO THAT IT WILL BY-PASS MAIN BUSS BAR.
- 15. ALL EMT RUNS SHALL BE GROUNDED AND HAVE A BUSHING, NO 26. INSTALL GROUND BUSHINGS ON ALL METALLIC CONDUITS AND PVC ABOVE GROUND.
- 16. USE SEPARATE HOLES FOR GROUNDING AT BUSS BAR. NO "DOUBLE-UP" OF LUGS.
- 17. POWER AND TELCO CABINETS SHALL BE GROUNDED (BONDED) TOGETHER.
- 18. NO LB'S ALLOWED ON GROUNDING.

- 19. PROVIDE STAINLESS STEEL CLAMP AND BRASS TAGS ON COAX AT ANTENNAS AND DOGHOUSE.
- 20 ALL ELECTRICAL AND GROUNDING AT THE CELL SITE SHALL COMPLY WITH THE NATIONAL ELECTRICAL CODE (NEC), NATIONAL FIRE PROTECTION ASSOCIATION (NFPA) 780 (LATEST EDITION), AND MANUFACTURER SPECIFICATION.
- 21 IF THE AC PANEL IN THE POWER CABINET IS WIRED AS SERVICE ENTRANCE, THE AC SERVICE GROUND CONDUCTOR SHALL BE CONNECTED
- TO GROUND ELECTRODE SYSTEM. WHEN THE AC PANEL IN THE POWER CABINET IS CONSIDERED A SUB-PANEL, THE GROUND WIRE SHALL BE
- INSTALLED IN THE AC POWER CONDUIT. THE INSTALLATION SHALL
- PER LOCAL AND NATIONAL ELECTRIC CODE (NFPA-70).
- 22 EXOTHERMIC WELDING IS RECOMMENDED FOR GROUNDING CONNECTION WHERE PRACTICAL. OTHERWISE, THE CONNECTION SHALL BE
- MADE USING COMPRESSION TYPE-2 HOLES. LONG BARREL LUGS OR DOUBLE CRIMP CLAMP "C" CLAMP. THE COPPER CABLES SHALL
- COATED WITH ANTIOXIDANT (COPPER SHIELD) BEFORE MAKING THE CONNECTIONS. THE MANUFACTURER'S TORQUING **RECOMMENDATIONS**
- ON THE BOLT ASSEMBLY TO SECURE CONNECTIONS SHALL BE FOLLOWED.
- 23 THE ANTENNA CABLES SHALL BE GROUNDED AT THE TOP AND BOTTOM OF THE VERTICAL RUN FOR LIGHTING PROTECTION. THE ANTENNA CABLE SHIELD SHALL BE BONDED TO A COPPER GROUND BUSS AT THE LOWER MOST POINT OF A VERTICAL RUN JUST BEFORE IT BEGINS TO BEND TOWARD THE HORIZONTAL PLANE. WIRE RUNS TO GROUND SHALL BE KEPT AS STRAIGHT AND SHORT AS POSSIBLE. ANTENNA CABLE SHIELD SHALL BE GROUNDED JUST BEFORE ENTERING THE CELL CABINET. ANY ANTENNA CABLES OVER 200 FEET IN LENGTH SHALL ALSO BE EQUIPPED WITH ADDITIONAL GROUNDING AT MID-POINT.
- 24 ALL GROUNDING CONDUCTORS INSIDE THE BUILDING SHALL BE RUN IN CONDUIT RACEWAY SYSTEM, AND SHALL BE INSTALLED AS STRAIGHT AS PRACTICAL WITH MINOR BENDS TO AVOID OBSTRUCTIONS. THE BENDING RADIUS OF ANY #2 GROUNDING CONDUCTOR IS 8". PVC RACEWAY MAY BE FLEXIBLE OR RIGID PER THE FIELD CONDITIONS. GROUNDING CONDUCTORS SHALL NOT MAKE CONTACT WITH ANY METALLIC CONDUITS, SURFACES OR EQUIPMENT.
- 25 PROVIDE PVC SLEEVES WHERE GROUNDING CONDUCTORS PASS THROUGH THE BUILDING WALLS AND /OR CEILINGS.
- BOND TO THE EQUIPMENT GROUND BUSS IN THE PANEL BOARD.
- 27 GROUND ANTENNA BASES, FRAMES, CABLE RACKS AND OTHER METALLIC COMPONENTS WITH #2 GROUNDING CONDUCTORS AND CONNECT TO INSULATED SURFACE MOUNTED GROUND BARS. CONNECTION DETAILS SHALL FOLLOW MANUFACTURER'S SPECIFICATIONS FOR GROUNDING.
- 28. ALL PROPOSED GROUNDING CONDUCTORS SHALL BE ROUTED AND CONNECTED TO THE MAIN GROUND BAR OR EXISTING GROUND RING.

KEY NOTES:


- $\langle 1 \rangle$ (E) ANTENNA GROUND BAR TO BE VERIFIED @ FIELD
- AWG 2 INSULATED COPPER GROUND WIRE FROM
- AWG 6 INSULATED COPPER GROUND WIRE FROM GROUND KIT TO (E) ANTENNA GROUND BAR

- REFER TO TYP. ANTENNA GROUNDING DIAGRAM
- 2. (E) GROUND WIRES ARE NOT SHOWN FOR CLARITY




ANTENNA GROUNDING PLAN

GROUNDING NOTES



KEY NOTES:

- (1) (E) EQUIPMENT GROUND BAR TO BE VERIFIED @ FIELD
- AWG 2 INSULATED COPPER TO (E) EQUIPMENT GROUND BAR
- (E) GROUND WIRES ARE NOT SHOWN FOR CLARITY.



EQUIPMENT GROUNDING PLAN



PREPARED FOR

5001 EXECUTIVE PKWY, SAN RAMON CA 94583

Vendor:

15 INFRASTRUCTURE 1150 BALLENA BLVD. UNIT 259 ALAMEDA, CA 94501

P-044379

AT&T Site ID:

CCL03263

08/03/20 COLORED ELEV MM3 100% CD 05/05/20 90% CD A 04/15/20 REV DATE DESCRIPTION

Licensor: SIGNED: 2020/08/04

EXPIRES: 2021/09/30 It is a violation of law for any

persons, unless they are acting under the direction of a licensed professional engineer, to alter this document

Issued For:

CCL03263

MORGAN HILL

1305 WEST DUNNE AVENUE MORGAN HILL, CA 95037

Sheet Title:

GROUNDING **PLANS & NOTES**

Sheet Number:

G-

TYP. ANTENNA GROUNDING DIAGRAM

